

20 MHz Analog/Digital Storage Oscilloscope



2522B

- 20MHz analog bandwidth
- 10MS/s sampling rate each channel
- 2k memory per channel
- 1GHz equivalent time sampling (at 0.1 μ s/div)
- Pre-trigger capture

Digital Mode Specifications

| | model 2522B |
|------------------------------------|---|
| Storage Word Size | 2048 x 8 bits/channel; (2 k/channel with direct sampling, 1 k/channel with equivalent time sampling). |
| Vertical Resolution | 1 in 256, approximately 25 steps/div. |
| Horizontal Resolution | 1 in 2048, approximately 200 samples/div. |
| Sampling Rate | 10 M samples/sec to 4 samples/sec, reduced in proportion to time base. Direct sampling at time base settings of 20 μ s/div and slower, equivalent time sampling at time base settings of 10 μ s/div and faster. |
| Time Base Expander | For storage of slow time events, time base steps 10 ms/div and slower have selectable 1/1 or 1/100 rate. 1/100 rate expands time base from 1 sec/div to 50 sec/div in 1-2-5 sequence. |
| Equivalent time Sampling Bandwidth | 20MHz for repetitive waveforms. |
| Dot Joining | Linear interpolation between samples. |

DIGITAL DISPLAY MODES

| | |
|--------------------|---|
| Roll | Stored data and display updated continually. |
| Refresh | Stored data and display updated by triggered sweep. |
| Hold | Freezes channel 1 and channel 2 data immediately. |
| Save CH 2 | Freezes channel 2 data immediately. |
| Pretrigger Storage | Available in single shot mode, switchable to 0% or 50%. |
| LED Indicators | Trigger (green), Arm (red), Pen Down (red). |

PLOT OUTPUT

| | |
|--|--|
| CH 1 and CH 2 Outputs OUTPUT and CH 2 OUTPUT | Selected by PLOT switch on rear panel. Output via CH 1 jacks on rear panel. Amplitude 0.1 V/div (1 V maximum). |
| Output Sweep Rate | Output sweep rate is 1/10 of TIME/DIV setting (and 1/100 switch when applicable). |
| Pen Lift Output | Available at Pen Down jack on rear panel. TTL high, Pen Up. TTL low, Pen Down. |

Analog Mode Specifications

VERTICAL AMPLIFIERS (CH 1 and CH 2)

| | |
|-----------------------|--|
| Sensitivity | 5 mV/div to 5 V/div in 1-2-5 sequence, 10 steps. Vernier control provides fully adjustable gain between steps. Pull x5 increases maximum sensitivity to 1 mV/div (at reduced bandwidth). |
| Accuracy | $\pm 3\%$, $\pm 5\%$ at x5 MAG |
| Input Resistance | 1M Ω $\pm 2\%$ |
| Input Capacitance | 25pF + 10pF |
| Frequency Response | 5 mV to 5 V/div: DC to 20 MHz (-3 dB), x5: DC to 10MHz (-3dB) |
| Rise Time | Approximately 17.5 ns (overshoot $\leq 3\%$) |
| Polarity Reversal | CH 2 only |
| Maximum Input Voltage | 400 V (DC + AC peak) |

MAXIMUM UNDISTORTED AMPLITUDE

| | |
|--------------|-------------|
| DC-to-20 MHz | 4 divisions |
| DC-to-10 MHz | 8 divisions |

OPERATING MODES

| | |
|--------------------------|------------------------------|
| CH 1: CH 1, single trace | CH 2: CH 2, single trace |
| ALT | Dual trace, alternating |
| CHOP | Dual trace, chopped |
| ADD | Algebraic sum of CH 1 + CH 2 |

SWEEP SYSTEM

| | |
|---------------------|---|
| Sweep Speed | 0.1 μ s/div to 2 s/div in 1-2-5 sequence, 23 steps. Vernier control provides fully adjustable sweep time between steps. |
| Accuracy: $\pm 3\%$ | Sweep Magnification: 10X, $\pm 6\%$ |
| Hold off | variable. |

TRIGGERING

| | |
|---|---|
| Modes: AUTO (free run) or NORM. Source: CH1, CH2, ALT, EXT, LINE. | |
| Maximum External Trigger Voltage: 200V (DC + AC peak). | |
| Sensitivity | Internal - 0.5 division, External - 500 mV. |

TRIGGER COUPLING

| | |
|-------------|---|
| AC | 30 Hz to 30 MHz. |
| TV H/HF: | Used for triggering from horizontal sync pulses. Low frequencies are attenuated. |
| TV V DC/LF: | Used for triggering from vertical sync pulses. High frequencies are attenuated. Direct coupled. |

HORIZONTAL AMPLIFIER (Input thru CH 1 Input)

| | |
|---------------------------|--|
| X-Y Mode | Switch selectable using X-Y switch |
| CH 1: X axis CH 2: Y axis | |
| Sensitivity | Same as vertical channel 1 |
| Accuracy | Y-Axis: $\pm 3\%$, X-Axis: $\pm 6\%$ |
| Input Impedance | Same as vertical channel 1 |
| Frequency Response | DC to 2 MHz typical (-3 dB) (to 6 divisions horizontal deflection) |
| X-Y Phase Difference | Approximately 3° at 50 kHz |
| Maximum Input Voltage | Same as vertical channel 1 |

Other Specifications

| | |
|----------------------|-------------------------------------|
| CRT | |
| Type | Rectangular with internal graticule |
| Display Area | 8 x 10 div (1 div = 1 cm). |
| Accelerating Voltage | 2 kV |
| Phosphor | P31 |
| Trace Rotation | Electrical, front panel adjustable |

ENVIRONMENT

| | |
|---------------------------|---|
| Within Specified Accuracy | 50° to 95°F (10° to + 35°C), 85% maximum RH |
| Full Operation | 32° to 104°F (0° to + 40°C), 85% maximum RH |
| Storage | -4° to 158°F (-20° to + 70°C) |

OTHER

| | |
|--------------------------------|---|
| CH 1 Output | (on rear panel) |
| Output Voltage | 25mV/div (nominal into 50 Ω load) |
| Output Impedance | Approximately 50 Ω |
| Frequency Response | 20 Hz to 10MHz, -3 dB into 50 Ω |
| Cal/Probe Compensation Voltage | 0.5 Vp-p + 3% square wave, 1kHz nominal |
| Power Requirements | 110 V/125/220/240 VAC, 50/60 Hz, approximately 60 W |
| Dimensions (HxWxD) | 5.2 x 12.8 x 15.6" (132 x 324 x 397 mm) |
| Weight | Approx. 19 lb (8.6 kg.) |

Accessories

Three Year Warranty

| | |
|-----------|--|
| SUPPLIED: | Instruction Manual, Two PR-33A x1/x10 Probes or equivalent, AC Power Cord, Spare Fuse |
| OPTIONAL: | PR-32A Demodulator Probe, PR-37A x1/x10/REF Probe, PR-100A x100 Probe, PR-55 High Voltage x1000 Probe, LC-210A Carrying Case |