

Data Sheet

**DC Regulated
Power Supplies**

Model 1665, 1666, 1667

- Over voltage protection, short circuit temperature
- Constant voltage operation
- Constant current operations
- Presetting current limiting value



Model 1666

| Specifications | Models | | |
|--------------------|------------------------------|------------|------------|
| | 1665 | 1666 | 1667 |
| Output Voltage: | 1-20VDC | 1-40VDC | 1-60VDC |
| Output Current: | 0-10A | 0-5A | 0-3.3A |
| Ripple & Noise: | 20mV | 20mV | 20mV |
| Load Regulation: | 0.5%+200mV | 0.5%+100mV | 0.5%+100mV |
| Line Regulation: | 20mV | 20mV | 20mV |
| Input Voltage: | 90-265VAC, 50/60Hz | | |
| Meter Type: | 3 ^{1/2} Digital LED | | |
| Meter Accuracy: | 1%+2 counts | | |
| Dimension (HxWxD): | 4.5" x 8" x 10.8" | | |
| Weight: | 6.6 lbs | | |

B&K Precision Corporation

22820 Savi Ranch Parkway, Yorba Linda, CA 92887
Tel: 714-921-9095, Fax: 714-921-6422
www.bkprecision.com

Specifications subject to change without notice